

**Birkbeck**  
**(University of London)**

**BSc/FD EXAMINATION**

**Department of Computer Science and Information Systems**

**Introduction to Computer Systems (BUCI008H4)**

**CREDIT VALUE: 15 credits**

**Summer 2019**

**Date of examination: Tuesday 11th June 2019**

**Duration of paper: 13.30–15.30**

There are **ten** questions in this paper.

Answer all **ten** questions.

Each question carries **ten** marks in total.

Calculators and other electronic devices are not permitted.

The examination is closed book.

No supplementary material is provided.

This paper is not prior disclosed.

1. (a) Multiply the decimal number 13 by the decimal number 17. (2 marks)
  - (b) Convert the decimal numbers 13 and 17 to the corresponding binary numbers. (2 marks)
  - (c) Add the two binary numbers obtained in part (b) of this question. Show any carries. (2 marks)
  - (d) Convert the decimal numbers 13 and 4 to the corresponding hexadecimal numbers. (2 marks)
  - (e) Add the two hexadecimal numbers obtained in part (d) of this question. (2 marks)
- 
2. (a) Let  $e$  be an integer in the range -4 to 3. The three bit excess notation for  $e$  is given by the standard binary representation for  $e + 4$ . Write out a table showing the three bit excess notation for integers in the range -4 to 3. (2 marks)
  - (b) Let  $e$  be an integer in the range -4 to 3. The three bit two's complement notation for  $e$  is given by the rightmost three bits of the standard binary representation of  $e + 8$ . Write out a table showing the three bit two's complement notation for integers in the range -4 to 3. (2 marks)
  - (c) Let  $E(e)$  be the three bit excess notation for an integer  $e$  in the range -4 to 3. Similarly, let  $TC(e)$  be the two's complement notation for  $e$ . Show that the bit string given by the rightmost three bits of  $E(2) + E(-1)$  is *not* equal to  $E(2 - 1)$ . Next, show that the bit string given by the rightmost three bits of  $TC(2) + TC(-1)$  is equal to  $TC(2 - 1)$ . (6 marks)

3. In this question the Boolean variable  $A$  has the value True (or 1) and the Boolean variable  $B$  has the value False (or 0). The value of the Boolean variable  $C$  is unknown.
- (a) Write out the truth table for the Boolean operator OR. (4 marks)
- (b) Show how the truth table in part (a) of this question can be used to obtain the value of the Boolean expression  $A$  OR  $B$ . (2 marks)
- (c) Evaluate the following expressions.
- i)  $(A \text{ AND NOT}(B)) \text{ OR } C$
  - ii)  $A \text{ AND } (2 == 1)$
  - iii)  $7 + 8 == 15$
  - iv)  $3 < 0$
- (4 marks)

4. The Brookshear floating point representation for a binary fraction  $x$  consists of eight bits, labeled  $s, e_1, e_2, e_3, m_1, m_2, m_3, m_4$  from left to right. If  $x$  is zero, then all eight bits are zero. If  $x$  is strictly negative, then the sign bit  $s$  is 1. If  $x$  is strictly positive, then the bit  $s$  is zero. Next, suppose  $x$  is not zero. To obtain the remaining seven bits,  $x$  is written in the form

$$\pm 2^r * 0.t$$

where  $r$  is an integer,  $0.t$  is a binary number and the leftmost bit of the bit string  $t$  is 1. The bits  $e_1, e_2, e_3$  together comprise the three bit excess notation for  $r$  and the bits  $m_1, m_2, m_3, m_4$  of the mantissa are the leftmost four bits of  $t$ .

- (a) Obtain the floating point representation for the decimal fraction  $-5/2$ . Show your working. In particular, show clearly the value of the integer  $r$  and the way in which this value is obtained. (6 marks)
- (b) Obtain the decimal representation for the number with the floating point representation 01111111. In particular, show clearly the value of the integer  $r$  and the way in which this value is obtained. (4 marks)

5. The table included below in this question describes instructions of length 16 bits, made by concatenating an op-code and an operand. The first four bits record the op-code. The remaining 12 bits record the operand. Four bits are required to specify a register  $R$  and eight bits are required to specify a memory location  $XY$ . Each register holds eight bits and each memory location holds eight bits.

Each 16 bit instruction is coded by four hexadecimal digits. For example, the four hexadecimal digits  $37A9$  specify an instruction with op-code 3, in which the 7 refers to register 7 and  $A9$  refers to the memory cell  $A9$ . The registers are numbered in hexadecimal from 0 to  $F$ .

All memory addresses in this question are given in hexadecimal notation.

Op-code	Operand	Description
1	$RXY$	Load register $R$ with the bit pattern in memory cell $XY$ .
2	$RXY$	Load register $R$ with the bit pattern $XY$ .
3	$RXY$	Store the bit pattern in register $R$ at memory cell $XY$ .
4	$ORS$	Move the bit pattern in register $R$ to register $S$ .
5	$RST$	Add (two's complement) the bit patterns in registers $S$ and $T$ . Put the result in register $R$ .
6	$RST$	Add (floating point) the bit patterns in registers $S$ and $T$ . Put the result in register $R$ .
7	$RST$	Or the bit patterns in registers $S$ and $T$ . Put the result in register $R$ .
8	$RST$	And the bit patterns in registers $S$ and $T$ . Put the result in register $R$ .
9	$RST$	Exclusive Or the bit patterns in registers $S$ and $T$ . Put the result in register $R$ .
A	$R0X$	Rotate the bit pattern in register $R$ one bit to the right $X$ times.
B	$RXY$	Jump: place the address $XY$ in the program counter if the bit pattern in register $R$ is equal to the bit pattern in register 0.
C	000	Halt.

- (a) State the op-code for the instruction 1192. Which register or registers are used when this instruction is carried out? (2 marks)

**Question 5 continues on the next page.**

- (b) **This is part (b) of question 5.** The following three instructions are performed.

1192

2280

8312

In what way does the final bit string in register 3 depend on the initial bit string in the memory location 92? (4 marks)

- (c) Assume that register 0 contains 00, memory cell 20 contains C0 and memory cell 21 contains 00. Append a fourth instruction to the three instructions in part (b) of this question to ensure that the machine halts if the final bit string in register 3 is 00.

(4 marks)

6. (a) Define the term *pointer* (2 marks)

- (b) Explain how the head pointer and the nil pointer are used in the formation of a linked list. (4 marks)

- (c) The top row of the following table shows 10 memory locations and three data items *A*, *B* and *C*. The second row of the table contains the addresses of the corresponding memory locations in the top row.

			<i>A</i>		<i>C</i>			<i>B</i>	
31	32	33	34	35	36	37	38	39	40

Copy the table into your script. Include in your copy of the table pointers in order to create a linked list in which the data items *A*, *B*, *C* occur in alphabetical order. The head of the linked list points to memory location 31. In your copy, the memory location immediately following a given data item should contain a pointer to the next item on the list, except for the last data item. (4 marks)

7. (a) Describe the way in which the data on a magnetic disk are arranged in tracks and sectors. Why do the tracks have their particular shape? (4 marks)

- (b) Define the terms *seek time*, *latency* and *access time*, as applied to a magnetic disk. (3 marks)

- (c) A magnetic disk has an access time of 12 milliseconds, i.e. 12/1000 seconds. The rate at which data can be read from the disk is 125 Megabytes a second. Find the size in Megabytes of a file for which the time to read the file is the same as the access time. (3 marks)

8. The following pseudo-code defines a function  $f$  which has as arguments two arrays  $A$  and  $B$  which have the same length. The entries in the array  $A$  are numbers. Each entry of  $B$  is either the number 0 or the number 1. Array indexing begins with 0.

```
function  $f(A, B)$ 
   $sum0 = 0$ 
   $sum1 = 0$ 
   $i = 0$ 
  while  $i < length(A)$ 
    if  $B[i] == 0$ 
       $sum0 = sum0 + A[i]$ 
    else
       $sum1 = sum1 + A[i]$ 
    endIf
     $i = i + 1$ 
  endWhile
  return  $sum1 - sum0$ 
endFunction
```

- (a) What is returned by the function  $f$  if it is called with  $A$  equal to  $[2, 4, -3]$  and  $B$  equal to  $[1, 0, 1]$  (2 marks)
- (b) Describe the way in which the return value of  $f$  is calculated in the general case, i.e.  $A$  and  $B$  satisfy the requirements given before the pseudo-code for  $f$  but no further information about  $A$  and  $B$  is available, except that the length of  $A$  is at least 1. (4 marks)
- (c) Suppose that the function  $f$  is called with arguments  $A1$  and  $B1$  such that  $A1$  and  $B1$  are arrays of the same length,  $A1$  contains numbers and each entry of  $B1$  is either the number -1 or the number 1. How is the return value of  $f$  calculated? Assume that the length of  $A1$  is at least 1. (4 marks)

9. The following code defines a function *pTriangle*.

```
function pTriangle(n)
    i = 1
    while i <= n
        print(" * ")
        i = i + 1
    endwhile
    print(newline)
    if n > 1
        pTriangle(n - 1)
    endif
endfunction
```

The function *pTriangle* prints a triangle of asterisks. For example, the function call *pTriangle*(3) yields

```
* * *
**
*
```

- (a) What feature of the code for *pTriangle* ensures that *pTriangle* is recursive? (2 marks)
- (b) What feature of the code for *pTriangle* ensures that *pTriangle* eventually halts? (2 marks)
- (c) Write pseudo-code for a function *pRow* that takes an integer  $n$  as an argument and prints out a row of  $n$  asterisks followed by a newline. It can be assumed that  $n \geq 1$ . (2 marks)
- (d) Write pseudo-code for a new function *pT* which is obtained by revising the pseudo-code for *pTriangle*. As part of the revision, the while loop in *pTriangle* is replaced by a function call to *pRow*. The printout from *pT* should be identical to the printout from *pTriangle*. (4 marks)

10. (a) Define the following terms in the context of the tables of data in a relational database.
- i) row (or tuple)
  - ii) attribute
  - iii) primary key
  - iv) foreign key
- (4 marks)
- (b) What is meant by the lossless decomposition of a table? (2 marks)
- (c) The table A is decomposed into the tables B and C, as shown below. Explain in detail why this decomposition is not lossless. (4 marks)

Table A:

name	department	tel. no.
Jones	Sales	555-2222
Smith	Sales	555-3333
Baker	Personnel	555-4444

Table B:

name	department
Jones	Sales
Smith	Sales
Baker	Personnel

Table C:

department	tel. no.
Sales	555-2222
Sales	555-3333
Personnel	555-4444